

PS-9116: 100v Line Loudspeaker Selector

The PS-9116 allows the selection of up to 16 individual loudspeakers/zones fed by a 100v amplifier or 2 groups of 8 loudspeakers fed by 2 separate amplifiers. Loudspeakers/zones are selected using switches with in-built LED indicators or groups can be activated via voltage-free contacts on the rear.

Features:

- 16 Individual zones
- LED indicator of selected zone
- Remote control of 2 x 8 groups via voltage-free contact
- 24v DC powered
- 1U high, 19" rack mounting

Specifications:

Model:	PS-9116:
Loudspeakers/Zones	16 Individual 2 x Groups of 8
Remote Control (All or 2 x Groups of 8)	Voltage-free contact ~ screw terminal on rear
Power Requirement	24v DC
Dimensions	482(W) x 44(H) x 280(D)mm
Weight	4kg

